



MOTOROLA

Consumer Systems Group

Order this document by
MCF5307/D
REV 0.0

MCF5307

Product Brief

MCF5307 Integrated ColdFire[®] Microprocessor

Overview

Introduction

The MCF5307 integrated microprocessor combines a ColdFire[®] processor core with the following components:

- 8K unified cache
- Multiply-Accumulate (MAC) unit and Divide unit
- DRAM controller
- DMA controller
- Timers
- M-Bus (I²C)¹
- Parallel and serial interface
- System integration unit

Designed for embedded control applications, the ColdFire core delivers enhanced performance (70 MIPS) while maintaining low system costs.

Performance boosts are supplied to the clock-doubled core through the on-chip, 8 Kbyte unified cache and 4K SRAM, which provide pipelined, single-cycle access to critical code and data.

The integrated Multiply-Accumulate (MAC) module enhances the device's functionality through support of high-speed, complex arithmetic operations. The MAC supports instruction issue rates of 1 multiply-accumulate per cycle for 16x16 operations, and also performs 32x32 operations, all producing a 32-bit result.

The MCF5307 processor greatly reduces the time required for system design and implementation by packaging common system functions on chip and providing glueless interfaces to 8-, 16-, and 32-bit DRAM, EDO DRAM, SDRAM, SRAM, ROM, FLASH, and I/O devices.

¹ I²C is a proprietary Philips bus.

This document contains information on a product under development. Motorola reserves the right to change or discontinue this product without notice.

SEMICONDUCTOR PRODUCT INFORMATION

Overview, Continued

ColdFire Architecture Provides New Price/Performance Levels

The revolutionary ColdFire microprocessor architecture gives cost-sensitive, high-volume markets new levels of price and performance. Based on the concept of variable-length RISC technology, ColdFire combines the architectural simplicity of conventional 32-bit RISC with a memory-saving, variable-length instruction set. In defining the ColdFire architecture for embedded processing applications, Motorola incorporated RISC architecture for peak performance and a simplified version of the variable-length instruction set found in the M68000 Family for code density.

Clock-Doubled Version 3 Core Boosts Performance

The MCF5307 is the first of the ColdFire Family to contain the Version 3, clock-doubled ColdFire microprocessor core. Increasing the internal speed of the core allows higher performance while providing the system designer with an easy-to-use external system interface.

ColdFire VL RISC Offers Many Advantages

By using a variable-length instruction set architecture, embedded system designers using ColdFire RISC processors will enjoy significant advantages over conventional fixed-length RISC architectures. The denser binary code for ColdFire processors consumes less valuable memory than any fixed-length instruction set RISC processor available. This improved code density means more efficient system memory use for a given application, and requires slower, less costly memory to help achieve a target performance level.

The MCF5307 Integrates a Rich Set of Modules with the ColdFire V3 Core

The integrated peripheral functions provide high performance and flexibility. The DRAM controller can interface with up to 256 Mbytes of DRAM and supports bursting, page-mode, EDO and synchronous DRAMs.

Serial communication channels are provided by two programmable full-duplex UARTs and an M-Bus (I²C interface-compatible) module. Four channels of DMA allow for fast data transfer using a programmable burst mode independent of processor execution. The two 16-bit general-purpose multimode timers provide separate input and output signals. For system protection, the processor includes a programmable 16-bit software watchdog timer. In addition, common system functions such as chip-selects, interrupt control, bus arbitration, and an IEEE 1149.1 JTAG module are included.

A sophisticated debug interface supports background-debug mode and real-time trace, with on-chip breakpoint registers accessible from an emulator or the processor itself. This interface is present in all ColdFire-based processors and allows common emulator support across the entire ColdFire Family.

MCF5307 Features

ColdFire Processor Core

- Variable-length RISC, clock-doubled Version 3 microprocessor core
 - Independent 4-stage instruction and 2-stage operand pipelines
 - 8-instruction FIFO buffer to provide decoupling between the pipelines
 - Branch acceleration unit for increased performance
 - 32-bit internal address bus with up to 4 Gbytes of linear address space
 - 32-bit data bus
 - 16 user-accessible, 32-bit-wide, general-purpose registers
 - Supervisor / User modes for system protection
 - Vector base register to relocate exception-vector table
 - Optimized for high-level language constructs
 - Hardware Integer Divide Unit
-

Multiply and Accumulate Unit

- Provides high-speed, complex arithmetic processing for DSP applications
 - 1 clock issue rate with 3-stage execute pipeline
 - Supports 16x16 and 32x32 multiplies, all with 32-bit accumulate
-

8 Kbyte Unified Cache

- Four-way set associative organization with writethrough and copyback modes
 - Operates at microprocessor core speed
 - Provides single-cycle access to critical code and data
-

4 Kbyte SRAM

- Programmable location within 4 Gbyte linear address space
 - Provides pipeline single cycle access to critical code and data
 - Information stored in SRAM not affected by RESET instruction
-

DMA Controller

- Four fully programmable channels
 - Supports dual-address and single-address transfers with 32-bit data capability
 - Two address pointers per channel that can increment or remain constant
 - 16-bit transfer counter per channel
 - Operand packing and unpacking supported
 - Auto-alignment transfers supported for efficient block movement
 - Supports bursting and cycle steal
 - Provides two clock-cycle internal access
-

DRAM Controller

- Supports up to 512 Mbytes of DRAM
 - Programmable refresh timer provides CAS-before-RAS refresh
 - Support for two separate memory banks
 - Support for EDO DRAMs and synchronous DRAMs
 - Support for external masters
-

MCF5307 Features, Continued

2 UARTs

- Full duplex operation
 - Flexible baud-rate generator
 - Modem control signals available ($\overline{\text{CTS}}$, $\overline{\text{RTS}}$)
 - Processor-interrupt capability
-

Dual 16-Bit General-Purpose Multimode Timers

- 8-bit prescaler
 - Timer input and output pins
 - Processor-interrupt capability
 - 22 ns resolution at 45 MHz
-

Motorola Bus (M-Bus) Module

- Interchip bus interface for EEPROMs, LCD controllers, A/D converters, keypads
 - Fully compatible with industry-standard I²C Bus
 - Master or slave modes support multiple masters
 - Automatic interrupt generation with programmable level
-

System Interface

- Glueless bus interface with chip selects and DRAM controller support for interface to 8-, 16-, and 32-bit DRAM, SRAM, ROM, FLASH, and I/O devices
 - 8 chip-select signals; 2 that are fully programmable with base address registers, 6 at a fixed offset off the chip-select base address register
 - Programmable wait states and port sizes
 - User-defined bus speed @ 1/2, 1/3, or 1/4 of processor clock
 - Programmable interrupt controller
 - Low interrupt latency
 - 4 external interrupt request inputs
 - Programmable autovector generator
 - 16-Bit general-purpose I/O interface
 - IEEE 1149.1 test (JTAG) module
-

System Debug Support

- Real-time trace for determining dynamic execution path
 - Background debug mode (BDM) for debug features while halted
 - Real-time debug support, including three user-visible hardware breakpoint registers
-

MCF5307 Features, Continued

On-Chip PLL

- Accepts input frequencies ranging from 16.67 to 45 MHz
- Generates 2X core clock and a bus clock of either 1/2, 1/3, or 1/4 the core clock based on user configuration at reset
- Supports low-power mode

Product Offerings


- 75 MIPS at 45 MHz (90 MHz clock-doubled internally)
- Offered at 90 MHz core clock with external bus capability of 45, 30, and 22.5 MHz (operating temperature: 0° to +70° C)
- Offered at 66.7 MHz core clock with external bus capability of 33.3, 22.2, and 16.7 MHz (operating temperature: 0° to +70° C and -40° to +85° C)
- Fully static 3.3-volt operation with 5V tolerant I/O pads
- 208 QFP package

MCF5307 Block Diagram

Overview of MCF5307 Components

Figure 1 is a block diagram of the MCF5307 processor. The paragraphs that follow provide an overview of the integrated processor components.

Figure 1: MCF5307 Block Diagram



ColdFire Processor Core

Overview

The ColdFire processor Version 3 core consists of two independent, decoupled pipelines to maximize performance while minimizing core size: the instruction fetch pipeline (IFP) and the operand execution pipeline (OEP).

Instruction Fetch Pipeline

The four-stage instruction fetch pipeline is for prefetching instructions. The IFP contains a branch acceleration unit that analyzes the prefetched instruction stream and takes a predicted branch to allow this pipeline to begin fetching the target path before the instruction is executed. This technique can improve the execution time of these change-of-flow instructions considerably. In addition, illegal instructions are decoded and an illegal instruction exception will be taken.

Operand Execution Pipeline

The prefetched instruction stream is gated into the two-stage operand execution pipeline, which decodes the instruction, fetches the required operands and executes the required function. Because the IFP and OEP are decoupled by an instruction buffer that serves as a FIFO queue, the IFP can prefetch instructions in advance of their actual use by the OEP, thereby minimizing time stalled waiting for instructions. The OEP is implemented in a two-stage pipeline featuring a traditional RISC datapath with a two-read/one-write port register file connected to these four execution units:

1. Arithmetic/logic unit
 2. Barrel shifter
 3. Integer divide
 4. MAC
-

MAC Module

The MAC unit provides high-performance DSP capabilities for the MCF5307. Integrated as an execution unit in the processor's operand execution pipeline, the MAC unit implements a 3-stage arithmetic pipeline with a sustained instruction issue rate of 1 multiply-accumulate per cycle for 16 x 16 operations (while also supporting 32 x 32 operations). The MAC opcodes provide a full-featured set of extensions to the standard ColdFire instruction set for signed and unsigned operands. In addition to executing the MAC-specific instructions, this unit also performs all integer multiply opcodes, providing higher performance for this class of operations.

8 Kbyte Unified Cache

The cache improves system performance by providing pipelined, single-cycle access to the processor core on references that hit in this memory. This decouples processor performance from system memory performance and increases bus availability for alternate bus masters, whether internal (the 4-channel DMA) or external.

The nonblocking design of the MCF5307 cache includes 16-byte line-fill buffers that allows processor-initiated requests that are mapped into this memory to be serviced while cache line-fill transfers are in progress. You can configure various memory address regions to operate as copyback or write-through cacheable regions, or as noncacheable spaces.

In addition to the 16 bytes of data, each cache line contains an address tag, and control bits. Support for a bursting interface quickly performs line-sized transfers in response to cache misses. A 4-entry, 32-bit-wide store buffer can decouple processor writes from the slower system bus interface to improve performance. The cache design, coupled with the processor microarchitecture, allows the MCF5307 to achieve 70 MIPS performance using a 90/45 MHz operating frequency.

Internal 4Kbyte SRAM

The 4 Kbyte on-chip SRAM is connected directly to the ColdFire core and provides pipelined single-cycle access to the address space mapped into this memory. Typically, this memory serves as the system stack. Additionally, you can map heavily referenced code segments or data variables into the SRAM to maximize performance. Users define the location of this memory within the 4 Gbyte linear address space of the processor.

DRAM Controller

The MCF5307 DRAM controller provides a glueless interface for as many as 2 banks of DRAM, each of which can be as large as 128 Kbytes up to 256 Mbytes. The controller supports 8-, 16-, or 32-bit memory widths. A unique addressing scheme allows for increases in system memory size without rerouting address lines and rewiring boards. The controller operates in normal mode or in page mode, and supports extended-data-out (EDO) DRAMs and synchronous DRAMs. At a 45 MHz external bus speed, the DRAM controller supports DRAMs with access times as fast as 22 ns.

DMA Controller

MCF5307 provides four fully programmable DMA channels for quick data transfer. Single- and dual-address mode is provided with the ability to program bursting and cycle steal. Data transfers are 32 bits in length with packing and unpacking supported along with an auto-alignment option for efficient block transfers.

UART Modules

Each UART on the MCF5307 contains an on-chip baud-rate generator, which provides both standard and nonstandard baud rates. Data formats can be 5, 6, 7, or 8 bits with even, odd, or no parity, and up to 2 stop bits in 1/16 increments. Four-byte receive buffers and two-byte transmit buffers minimize CPU service calls. The UART modules also provide several error-detection and maskable-interrupt capabilities. Modem support includes request-to-send ($\overline{\text{RTS}}$) and clear-to-send ($\overline{\text{CTS}}$) lines.

The system clock provides the clocking function via a programmable prescaler. Full duplex, auto-echo loopback, local loopback, and remote loopback modes let you test UART connections. The programmable UARTs can interrupt the CPU on various normal or error-condition events.

Timer Module

The timer module includes two general-purpose timers, each of which contains a free-running 16-bit timer for use in any of three modes. One mode captures the timer value with an external event. Another mode triggers an external signal or interrupts the CPU when the timer reaches a set value, while a third mode counts external events.

The timer unit has an 8-bit prescaler that allows programming of the clock input frequency, which is derived from the system clock or an external clock input pin (TIN). The programmable timer-output pin generates either an active-low pulse or toggles the output.

Motorola Bus (M-Bus) Module

The M-Bus interface is a two-wire, bidirectional serial bus that exchanges data between devices and is compliant with the I²C Bus standard. The M-Bus minimizes the interconnection between devices in the end system and is best suited for applications that need occasional bursts of rapid communication over short distances among several devices.

System Interface

Overview

The MCF5307 processor provides a glueless interface to 8-, 16-, and 32-bit port size FLASH, SRAM, ROM, and peripheral devices with independent programmable control of the assertion and negation of chip-selects and write-enables. The MCF5307 also supports bursting ROMs. The MCF5307 has a clock-multiplied core that operates at 2x, 3x, or 4x the external bus frequency. You select the multiplier for the bus frequency at reset of the microprocessor.

External Bus Interface

The bus interface controller transfers information between the ColdFire core or DMA and memory, peripherals, or other devices on the external bus. The external bus interface provides 32 bits of address bus space, a 32-bit data bus, and all associated control signals. This interface implements an extended synchronous protocol that supports bursting operations.

Simple two-wire request/acknowledge bus arbitration between the MCF5307 processor and another bus master, such as an external DMA device, is glueless with arbitration logic internal to the MCF5307 processor. Multiple-master arbitration is also available with some external arbitration logic.

Chip-Selects

Eight chip-select outputs (2 that are programmable with base address registers, 6 at fixed offsets from the chip-select bus address register) provide signals that enable external memory and peripheral circuits with automatic wait-state insertion. These signals interface to 8-, 16-, or 32-bit ports. The base address, access permissions, and internal bus transfer terminations are programmable with configuration registers.

16-Bit Parallel Port Interface

A 16-bit general-purpose programmable parallel port serves as either an input or an output on a bit-by-bit basis.

System Interface, Continued

Interrupt Controller

The interrupt controller provides user-programmable control of 10 internal peripheral interrupts and implements 4 external fixed interrupt-request pins. You can program each internal interrupt to any one of 7 interrupt levels and 4 priority levels within each of these levels and can program the external interrupt request pins to level 1, 3, 5, and 7 or levels 2, 4, 6, and 7. Autovector capability is available for internal and external interrupts.

JTAG

To help with system diagnostics and manufacturing testing, the MCF5307 processor includes dedicated user-accessible test logic that complies with the IEEE 1149.1a standard for boundary-scan testability, often referred to as Joint Test Action Group, or JTAG. For more information, refer to the IEEE 1149.1a standard.

System Debug Interface

The ColdFire processor core debug interface supports real-time trace and debug, along with background debug mode (BDM). The BDM interface is implemented using a serial communication channel with an emulator. The BDM is compatible with the BDM interface provided on Motorola's 683XX Family of parts.

To support real-time trace, four output bits (PST) provide status information on processor activity on a cycle-by-cycle basis. Additionally, a 4-bit output data bus (DDATA) can be configured to display operand data and certain change-of-flow target addresses for determining the dynamic execution path through the application.

Finally, the Debug module provides a number of on-chip breakpoint registers that can be configured by an emulator, or by the processor itself to generate special debug interrupts or processor halts. The breakpoint resources include two 32-bit address registers, a 32-bit PC and 32-bit PC mask registers, and a 32-bit data register and 32-bit data mask register. These breakpoint registers can be configured in single- or double-level triggers where you define the trigger response.

PLL Module

Overview

The MCF5307 PLL module has three modes of operation:

1. Normal mode
 2. Reduced power mode
 3. Reset mode
-

Normal Mode Input Frequency

In normal mode, an input frequency to the MCF5307 can range from 16.67 MHz to 45 MHz. This input frequency is programmed at reset and clock-doubled to provide the processor clock and then is divided down to provide the bus clock output. The bus clock is programmed to 1/2, 1/3, or 1/4 of the core clock.

Reduced Power Mode

In reduced power mode, the PLL core clock is shut off by a combination of executing the STOP instruction and programming a control bit in the System Configuration register. This low-power mode allows the core to be turned off while retaining the core register contents.

Reset Mode

When the MCF5307 $\overline{\text{RESET}}$ pin is asserted, the PLL enters reset mode. At reset, the PLL asserts $\overline{\text{RESETO}}$ to the rest of the processor and as an external pin from the MCF5307. The system input frequency range, MCF5307 bus clock frequency (along with other MCF5307 configuration information) are all sampled during reset mode.

Programming Model, Instruction Set, and Addressing Mode

Overview

The ColdFire programming model is separated into two privilege modes: supervisor and user. The S-bit in the status register (SR) indicates the current privilege mode. The processor identifies a logical address by accessing either the supervisor or user address space, which differentiates between supervisor and user modes.

Supervisor Mode

Supervisor mode protects system resources from uncontrolled access by users. In supervisor mode, you can access all registers and execute all ColdFire instructions. Operating system functions (including I/O control) are performed while in supervisor mode. During exception processing, the processor enters supervisor mode regardless of the operating mode at the time of the exception.

Typically, system programmers use the supervisor programming model to implement operating system functions and provide I/O control. The supervisor programming model provides access to the same registers as the user model, plus seven additional registers. These added resources include the upper byte of the Status Register (SR), the Vector Base Register (VBR), plus five registers defining the configuration and attributes of the address space connected to the MCF5307.

User Mode

While in user mode, access to only a subset of the supervisor registers is allowed, and execution of privileged instructions is not permitted. Typically, most application processing occurs while in user mode. Entry into user mode is usually accomplished by executing a “return from exception” (RTE) or MOVE, SR instruction.

User Programming Model

The registers depicted in the programming model (see Figure 2) provide high-speed storage for data and addresses for the ColdFire processor core. The user programming model consists of sixteen general-purpose 32-bit registers {D0-D7, A0-A7} plus two additional registers: the program counter (PC) and the condition code register (CCR).

The program counter is a 32-bit register containing the address of the instruction currently being executed by the MCF5307 processor. The 8-bit CCR contains indicator flags that reflect the result of a previous operation and are used for conditional instruction execution.

Programming Model, Instruction Set, and Addressing Mode, Continued

Status Register (SR) The upper byte of the Status Register provides interrupt information in addition to a variety of mode indicators signaling the operating state of the ColdFire processor.

Vector Base Register (VBR) The VBR defines the upper 12 bits of the base address of the exception vector table used during exception processing. The low-order 20 bits are forced to zero, placing the vector table on a 0-modulo-1Mbyte address boundaries, which is set by the upper 12 bits of the address.

Cache Control Register (CCR) The Cache Control Register (CACR) defines the configuration of the unified cache and provides a set of default address attributes.


Access Control Registers (ACRs) There are two Access Control Registers (ACR0, ACR1), which each define a set of address attributes for a specific memory space. For example, a memory space can be defined as copyback, writethrough, or noncacheable using the ACR registers.

RAM Base Address Register (RAMBAR) The RAM Base Address Register (RAMBAR) provides the logical base address for the processor's 4 Kbyte SRAM module as well as definition of those access types that are allowed to access that SRAM.

Module Base Address Register (MBAR) The Module Base Address Register (MBAR) defines the logical base address for the memory-mapped space containing the control registers for the on-chip peripherals.

Programming Model, Instruction Set, and Addressing Mode, Continued

Figure 2. ColdFire Programming Model



Programming Model, Instruction Set, and Addressing Mode, Continued

Data Format Summary

Operands can be signed or unsigned and are contained in registers, memory, or the instructions themselves. The operand specifiers and size for each operation are either explicitly encoded in the instruction or implicitly defined by the instruction's definition. Table 1 summarizes the MCF5307 data formats.

Table 1: MCF5307 Data Formats

OPERAND DATA FORMAT	SIZE
Bit	1 Bit
Byte	8 Bits
Word	16 Bits
Longword	32 Bits

Notational Conventions

The following tables list the commonly used ColdFire notational conventions.

REGISTER SPECIFICATION	
An	Any Address Register n (example: A3 is address register 3)
Ay, Ax	Source and destination address registers, respectively.
Dn	Any Data Register n (example: D5 is data register 5)
Dy, Dx	Source and destination data registers, respectively.
Rc	Control Register (example: VBR, CACR)
Rn	Any Address or Data Register n
Ry, Rx	Any source and destination registers, respectively.
Rw	Destination Register w (used on certain MAC instructions only)
Xi	Index Register i (Can be an address or data register: A, Di)

REGISTER NAMES	
CCR	Condition Code Register (lower byte of status register)
MACSR	MAC Status Register
PC	Program Counter
Racc	MAC Accumulator Register
Rmask	MAC Mask Register
SR	Status Register
DATA SIZE AND TYPE	
<size>	Operand Data Size: Byte (B), Word (W), Longword (L).
B, W, L	Specifies a signed integer data type of 8-bit byte, 16-bit word, or 32-bit longword.

SUBFIELDS AND QUALIFIERS	
#<data>	Immediate data following the 16-bit instruction word of the instruction
#<list>	List of registers for MOVEM instruction (example: D3-D0 = D3, D2, D1, D0)
#<vector>	Identifies a 4-bit vector number for TRAP instructions
()	Identifies an indirect operand address referencing memory
(xxx)	Identifies an absolute address referencing memory
<ea>	Effective address
<ea>y	Source effective address
<ea>x	Destination effective address
<label>	Assembly language program label
d _n	Signed displacement Value, n Bits Wide (example: d ₁₆ is a 16-bit displacement).
+	Postincrement indicator
-	Predecrement indicator
SF	Scale factor (x1, x2, or x4 for indexed addressing modes, <<1 or >>1 for MAC ops)

Addressing Capability Summary

The MCF5307 processor supports seven addressing modes (refer to Table 2a). The register indirect addressing modes support postincrement, predecrement, offset, and indexing, which are particularly useful for handling data structures common to sophisticated embedded applications and high-level languages. The program counter indirect mode also has indexing and offset capabilities. This addressing mode is typically required to support position-independent software. As part of the indexed addressing mode, ColdFire supports an optional scale factor which can be applied to the index register to easily access byte, word or longword entries within an array (x1, x2, x4).

Addressing Capability Summary, Continued

Effective Addressing Modes

An instruction's effective addressing mode can specify the operand in one of three ways:

1. It can specify the data value directly as an immediate operand
2. It can specify the register containing the operand
3. It can specify the addressing calculation needed to reference the memory location containing the operand

Each addressing mode has a unique assembler syntax. In addition to the generalized format where the addressing mode is specified directly in the instruction, there are some opcodes where the effective address is implicitly defined by the operation itself. Table 2a summarizes the effective addressing modes of ColdFire processors; Table 2b shows specific effective addressing modes for the MOVE instruction; and Table 2c presents addressing variants used by certain instructions.

Table 2a: ColdFire Effective Addressing Modes

ADDRESSING MODES	SYNTAX
Register Direct Data Address	Dn An
Register Indirect Address Address with Postincrement Address with Predecrement Address with Displacement	(An) (An)+ -(An) (d16,An)
Address Register Indirect with Scaled Index 8-Bit Displacement	(d ₈ ,An,Xi*SF)
Program Counter Indirect with Displacement	(d ₁₆ ,PC)
Program Counter Indirect with Scaled Index 8-Bit Displacement	(d ₈ ,PC,Xi*SF)
Absolute Data Addressing Short Long	(xxx).W (xxx).L
Immediate	#<data>

Table 2b: Specific Effective Addressing Modes for MOVE Instructions

SOURCE <EA>	DESTINATION <EA>
Dy	All
Ay	All
(Ay)	All
(Ay)+	All

Table 2b: Specific Effective Addressing Modes for MOVE Instructions (Continued)

SOURCE <EA>	DESTINATION <EA>
-(Ay)	All
(d ₁₆ ,Ay) (d ₁₆ ,PC)	Dx Ax (Ax) (Ax)+ -(Ax) (d ₁₆ ,Ax)
(d ₈ ,Ay,Xi*SF) (d ₈ ,PC,Xi*SF)	Dx Ax (Ax) (Ax)+ -(Ax)
(xxx).W (xxx).L	Dx Ax (Ax) (Ax)+ -(Ax)
#<data>	Dx Ax (Ax) (Ax)+ -(Ax)

Table 2c: Addressing Variants Used By Certain Instructions

ADDRESSING VARIANT	ALLOWABLE MODES
<ea-1>	Dn (An) (An)+ -(An) (d ₁₆ ,An)
<ea-2>	(An) (d ₁₆ ,An)
<ea-3>	(An) (d ₁₆ ,An) (d ₈ ,An,Xi*SF) (xxx).W (xxx).L (d ₁₆ ,PC) (d ₈ ,PC,Xi*SF)

Instruction Set

Overview

The ColdFire instruction set supports high-level languages and is optimized for those instructions most commonly generated by compilers in embedded applications. Tables 3a and 3b provide an alphabetized listing of the ColdFire instruction set opcode, supported operation sizes, and assembler syntax. For two-operand instructions, the first operand in the syntax is generally the source operand, and the second operand is the destination.

Table 3a: Supervisor Mode Instruction Summary

OPCODE	SUPPORTED OPERAND SIZES	ADDRESSING MODES
CPUSHL	Unsize	(An)
HALT*	Unsize	
MOVE from SR	.W	SR,Dx
MOVE to SR	.W	Dy,SR #<data>,SR
MOVEC	.L	Ry,Rc
RTE	Unsize	
STOP	.W	#<data>
WDEBUG	.L	<ea-2>
*The HALT instruction can be configured to allow user mode execution by setting the UHE bit in the debug module's Configuration/Status Register (CSR).		

Table 3b: User Mode Instruction Summary

OPCODE	SUPPORTED OPERAND SIZES	ADDRESSING MODES
ADD	.L	<ea>y,Dx Dy,<ea>x
ADDA	.L	<ea>y,Ax
ADDI	.L	#<data>,Dx
ADDQ	.L	#<data>,<ea>x
ADDX	.L	Dy,Dx
AND	.L	<ea>y,Dx Dy,<ea>x
ANDI	.L	#<data>,Dx
ASL	.L	Dy,Dx #<data>,Dx
ASR	.L	Dy,Dx #<data>,Dx
Bcc	.B,.W	<label>
BCHG	.B,.L	Dy,<ea>x #<data>,<ea-1>x
BCLR	.B,.L	Dy,<ea>x #<data>,<ea-1>x
BRA	.B,.W	<label>

Table 3b: User Mode Instruction Summary
(Continued)

OPCODE	SUPPORTED OPERAND SIZES	ADDRESSING MODES
BSET	.B,.L	Dy,<ea>x #<data>,<ea-1>x
BSR	.B,.W	
BTST	.B,.L	Dy,<ea>x #<data>,<ea-1>x
CLR	.B,.W,.L	<ea>x
CMP	.L	<ea>y,Dx
CMPA	.L	<ea>y,Ax
CMPI	.L	#<data>,Dx
DIVS	.W	<ea>y, Dx
DIVS	.L	<ea-1>y, Dx
DIVU	.W	<ea>y, Dx
DIVU	.L	<ea-1>y, Dx
EOR	.L	Dy,<ea>x
EORI	.L	#<data>,Dx
EXT	.W,.L	Dx
EXTB	.L	Dx
JMP	Unsize	<ea-3>y
JSR	Unsize	<ea-3>y
LEA	.L	<ea>y,Ax
LINK	.W	Ax,#<d16>
LSL	.L	Dy,Dx #<data>,Dx
LSR	.L	Dy,Dx #<data>,Dx
MAC	.W,.L	Ry, RxSF
MAC	.W,.L	Rx, RySF,<ea-1>y, Rw
MOVE	.B,.W,.L	see MOVE Table
MOV	.L	Ry,MACSR #<data>,MACSR Ry,Racc #<data>,Racc Ry,Rmask #,data>,Rmask MACSR,CCR MACSR,Rx Racc,Rx Rmask,Rx
MOVE from CCR	.W	CCR,Dx
MOVE to CCR	.W	Dy,CCR #<data>,CCR
MOVEM	.L	<ea-2>y,#<list> #<list>,<ea-2>x
MOVEQ	.L	#<data>,Dx
MSAC	.W,.L	Ry, RxSF
MSAC	.W,.L	Rx, RxSF,<ea-1>y, Rw
MULS	.W	<ea>y,Dx
MULS	.L	<ea-1>y,Dx
MULU	.W	<ea>,Dx
MULU	.L	<ea-1>y,Dx

**Table 3b: User Mode
Instruction Summary
(Continued)**

OPCODE	SUPPORTED OPERAND SIZES	ADDRESSING MODES
NEG	.L	Dx
NEGX	.L	Dx
NOP	Unsize	
NOT	.L	Dx
OR	.L	<ea>y, Dx Dy, <ea>x
ORI	.L	#<data>, Dx
PEA	.L	<ea-3>y
PULSE	Unsize	
REMS	.L	<ea-1>, Dx
REMU	.L	<ea-1>, Dx
RTS	Unsize	
Sc	.B	Dx
SUB	.L	<ea>y, Dx Dy, <ea>x
SUBA	.L	<ea>y, Ax
SUBI	.L	#<data>, Dx
SUBQ	.L	#<data>, <ea>x
SUBX	.L	Dy, Dx
SWAP	.W	Dx
TRAP	Unsize	#<vector>
TRAPF	Unsize	
TRAPF	.W, .L	#<data>
TST	.B, .W, .L	<ea>y
UNLK	Unsize	Ax
WDDATA	.B, .W, .L	<ea>y

General Device Information


**Table 4: MCF5307
Package/Frequency
Availability**

PACKAGE	OPERATING TEMP.	FREQUENCY
208 QFP	0 to 70 C, -40 to +85 C	66.7 MHz core w/16.7, 22.2, & 33.3 MHz bus capability
208 QFP	0 to 70 C	90 MHz core w/ 22.5, 30, & 45MHz bus capability

Documentation

Additional and detailed information is available from Motorola literature distribution centers. To find out more about Motorola's ColdFire products and development tool offerings, please visit our website at <http://www.mot.com/coldfire>.

DOCUMENT NUMBER	DOCUMENT TITLE
MCF5307 Specification	<i>MCF5307 Spec. Rev. 0.0</i> (Available through secure website. Contact your local salesperson for access)
MCF5307UM/AD	<i>MCF5307 User's Manual</i> (Est. Stocking 1Q98)
5200PRM/AD Rev1	<i>MCF5200 ColdFire Family Programmer's Reference Manual</i>

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters can and do vary in different applications. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

Literature Distribution Centers:

USA/EUROPE: Motorola Literature Distribution; P.O. Box 20912, Arizona 85036.

JAPAN: Nippon Motorola Ltd.; 4-32-1, Nishi-Gotanda, Shinagawa-ku, Tokyo 141 Japan.

ASIA-PACIFIC: Motorola Semiconductors H.K. Ltd.; Silicon Harbour Center, No. 2 Dai King Street, Tai Po Industrial Estate, Tai Po, N.T., Hong Kong.

*Digital DNA

MCF5307 : Integrated ColdFire Version 3 Microprocessor

The MCF5307 is a high performance (70 MIPS), low-cost, highly integrated microprocessor, designed for embedded control applications, which combines a Version 3 ColdFire® processor core with a Multiply Accumulate (MAC) unit, DRAM controller, DMA controller, timers, and parallel and serial interfaces. The time required for system design and implementation is greatly reduced by packaging common system functions on chip and providing glueless interfaces to 8-, 16-, and 32-bit DRAM, SRAM, ROM, and I/O devices. Support for EDO DRAM and Synchronous DRAM is also present.

- [Block Diagram](#)

Page Contents

- [Features](#)
- [Parametrics](#)
- [Documentation](#)
- [Development Tools/Boards](#)
- [Design Tools](#)
- [Orderable Parts](#)

Other Info

- [Where to Buy](#)
- [FAQs](#)

Products

[Microcontrollers](#)

[Microprocessors](#)

[32-Bit \(68K, ColdFire, C-Port, MCore, PowerPC, ARM\)](#)

[ColdFire MCF5XXX](#)

[Related Links 68K/ColdFire Site](#)

MCF5307 Features

- 4 KByte SRAM
- Multiply-Accumulate (MAC) unit and Divide unit
- 8 KByte Unified Cache
- 4-channel DMA controller
- DRAM Controller, supports SDRAM, EDO and page node DRAM
- 2 Universal Synchronous/Asynchronous Receiver/Transmitters (UART)
- Dual 16-Bit General-Purpose Multimode Timers
- I²C®-Compatible Bus
- System Interface
- System Debug Support
- Clock Multiplied PLL
- 16-bit general-purpose parallel I/O port
- 70 MIPS at 90 MHz
- Available at 66 and 90 MHz

[\[top\]](#)

MCF5307 Parametrics

Frequency (MHz)	V Voltage (Volts)	Power Dissipation (Typ) (Watts)	Performance (Max) (MIPS)	Bus Interface (Bits)	Cache-L1 Inst/Data (KBytes)	Memory (KBytes)	Process	Package
66, 90	3.3V	0.95W	70	32-Bits, Dynamic	8K Unified	4K SRAM	0.35u TLM	208 TQFP

[\[top\]](#)

MCF5307 Documentation

Application Note

ID	Name	Format	Size K	Rev #	Date Last Modified
AN2008/D	Evaluating ColdFire in a 68K Target System: MCF5307 to MC68EC020 Gateway Reference Design	pdf	149	0	7/14/2000
AN1766/D	Using the SDRAM Controller on the MCF5307 ColdFire Integrated Processor Application Note	pdf	131	2.0	3/12/1999
AN1802/D	MCF5307 Connecting the MCF5307 to 168-Pin Unbuffered SDRAM DIMMs 68K ColdFire Microprocessors	pdf	53	0.1	5/30/1999

Brochure

ID	Name	Format	Size K	Rev #	Date Last Modified
MCF5XXXBR	MCF5XXXBR BROCHURE : Motorola's ColdFire Microprocessor Architecture: Setting the Standard for the Future	pdf	398	0	1/01/1999

Fact Sheets

ID	Name	Format	Size K	Rev #	Date Last Modified
MCF5XXXWP	MCF5XXXWP WHITE PAPER: Motorola ColdFire VL RISC Processors	pdf	35	0	8/01/1996

Miscellaneous

ID	Name	Format	Size K	Rev #	Date Last Modified
MCF5307/D	MCF5307 MCF5307 Integrated ColdFire Microprocessor	pdf	82	0	1/01/1997
MCF5307ER/D	MCF5307 Errata to MCF5307	pdf	304	4	6/15/2000

Product Change Notices

ID	Name	Format	Size K	Rev #	Date Last Modified
PCN5228	Introduction of New MCF5307 Mask, 2J20C	html	13	-	11/10/1999
PCNR00320	Moisture Sensitivity Level change for 144 TQFP Products - PCN# R00320	html	8	-	7/13/1996
PCNR00315	Shrink Wrapping Tray Products	html	10	-	-
PCN5521	XCF5307 Final Test Transfer to KLM PCN#5521	txt	2	-	-
PCN5547	Shrink Wrap Alternate Process PCN#5547	txt	3	-	3/31/2000
PCN5589	XCF5307 Assembly Transfer to Anam, PCN #5589	txt	2	-	4/24/2000
PCN5628	MOS11 CDR2 .32um Optimized Metallization - PCN #5628	txt	5	-	6/12/2000

Quality Information

ID	Name	Format	Size K	Rev #	Date Last Modified
REL4Q98QI	Product Reliability Information 4Q98	pdf	160	-	12/31/1998
PRODRELQI	Product Reliability Information (2Q97-3Q98)	html	4	-	12/31/1998

Reference Manual

ID	Name	Format	Size K	Rev #	Date Last Modified
MCF5307BUM	MCF5307 User's Manual - Mask Set J20C (new mask)	pdf	5352	-	7/07/2000
MCF5307AUM	MCF5307 User's Manual - Mask Set H55J	html	15	-	-
MCF5307UMMSAD/AD	MCF5307 MCF5307 User Manual Mask Set Addendum	pdf	124	0.5	8/05/1999
CFPRM/D	ColdFire Family Programmer's Reference Manual	pdf	3691	2	7/26/2001
MCF5307ASECUM	MCF5307 User's Manual (H55J Mask) - by Sections	html	15	-	-
MCF5307BSECUM	MCF5307 User's Manual (J20C Mask) - by Section	html	20	-	-
MCF5307BUMER	MCF5307 User's Manual Errata	pdf	38	-	1/02/2001

Reports or Presentations

ID	Name	Format	Size K	Rev #	Date Last Modified
EMBSOLTNS	Embedded Solutions for a Digital World	html	3	-	-
CFDVTAR	Design, Verification, and Test of the ColdFire Embedded Microprocessors (1997 Symposium)	pdf	143	-	-
5307EXCMPRAR	EXCERPT FROM "Integration, Diversification Key for 1998", Microprocessor Report	html	1	-	1/25/1999

Selector Guide

ID	Name	Format	Size K	Rev #	Date Last Modified
SG175	SG175 Networking and Computing Systems Group Selector Guide for 3rd Quarter 2001	pdf	954	16	7/23/2001
SG186/D	Microcontroller Selector Guide Quarter 4, 2001	pdf	1342	9	9/28/2001

Training

ID	Name	Format	Size K	Rev #	Date Last Modified
MCF5307TR	MCF5307 Technical Overview and Training	html	6	-	-
MCF5307SDRAMTR	MCF5307 SDRAM Worksheet	pdf	58	-	-

White Paper

ID	Name	Format	Size K	Rev #	Date Last Modified
----	------	--------	--------	-------	--------------------

MCF5XXXDSPWP	MCF5XXXDSP Digital Signal Processing on the ColdFire Architecture	pdf	37	0	1/01/1999
MCF5XXXDBWP	MCF5XXXDBWP Debug Support on the ColdFire Architecture	pdf	36	0	1/01/1999

[\[top\]](#)

MCF5307 Development Tools/Boards

ID	Name	Vendor ID
M5307C3	Matrix Design Evaluation System for MCF5307	MOTOROLA
M5307PROMO	Promotional Development Kit for the MCF5307 Includes the Arnewsh Evaluation Board	MOTOROLA

[\[top\]](#)

Design Tools

Bridges

ID	Name	Vendor ID	Format	Size K	Rev #
V360EPC	V3 Semiconductors' PCI Bridge	MOTOROLA	html	3	-

Converters

ID	Name	Vendor ID	Format	Size K	Rev #
PORTASM68K	MicroAPL Limited's ColdFire Assembler Converter -- FREE!	MOTOROLA	html	1	1.2.7

Libraries

ID	Name	Vendor ID	Format	Size K	Rev #
CF68KLIB	MicroAPL Limited's Emulation Library -- FREE!	MOTOROLA	html	1	-

Miscellaneous

ID	Name	Vendor ID	Format	Size K	Rev #
MCF5307DMACOD	MCF5307 Sample Assembly Code - Initializes and Tests 5307 DMA Controller	MOTOROLA	txt	1	-
MCF5XXXSC	ASCII TEXT FOR FFT, DCT Source Codes	MOTOROLA	html	0	-
MCF5307INITCOD	MCF5307 Sample Initialization Code - Good example of initializing 5307. Contains C and assembly code. Uses timer module.	MOTOROLA	zip	13	-
MCF5307STOPCOD	MCF5307 Sample Assembly Code - Examples Using Stop Instruction and Interrupts	MOTOROLA	txt	2	-
3PTOOLSDEV	68K/ColdFire Third-Party Tools Support Listing 68K/ColdFire 3-Party Tools Vendors	MOTOROLA	html	51	-
MCF5307TIMECOD	MCF5307 Sample Assembly Code - Sample Code that Initializes and Tests 5307 Timer Modules	MOTOROLA	txt	4	-
MCF5XXXPERL	Perl Script to Postprocess FFT Data	MOTOROLA	html	0	-
DBUGFIRM	dBUG Firmware Development	MOTOROLA	html	21	-
MCF5307UARTCOD	MCF5307 Sample Assembly Code - Sample Code that Initializes and Tests 5307 UARTs.	MOTOROLA	txt	4	-

MCF5307JMCOD	MCF5307 executable object code for the 5307jm.s file. Can be directly downloaded to the 5307 development system for testing and debugging	MOTOROLA	s	82	-
------------------------------	---	----------	---	----	---

Models

ID	Name	Vendor ID	Format	Size K	Rev #
MCF5307IBIS	MCF5307 IBIS Model--New Mask	MOTOROLA	txt	100	1.0

Software

ID	Name	Vendor ID	Format	Size K	Rev #
MCF5307BSDL	MCF5307 BSDL	MOTOROLA	txt	19	-

[\[top\]](#)

Orderable Parts Information

PartNumber	Package Info	Life Cycle Description (code)	Remarks
MCF5307FT66B	208-Lead Plastic Flat Pack (28x28mm)	PRODUCT NEWLY INTRO'D/RAMP-UP(1)	V3 ColdFire w/ MAC, DMA, SDRAM, DUART
MCF5307FT90B	208-Lead Plastic Flat Pack (28x28mm)	PRODUCT NEWLY INTRO'D/RAMP-UP(1)	V3 ColdFire w/ MAC, DMA, SDRAM, DUART
MCF5307CFT66B	208-Lead Plastic Flat Pack (28x28mm)	PRODUCT NEWLY INTRO'D/RAMP-UP(1)	Ext Temp, V3 ColdFire w/ MAC, DMA, SDRAM, DUART
SPAK5307FT66B	208-Lead Plastic Flat Pack (28x28mm)	PRODUCT RAPID GROWTH(2)	Sample Pack
SPAK5307FT90B	208-Lead Plastic Flat Pack (28x28mm)	PRODUCT MATURITY/SATURATION(4)	Sample Pack
SPAK5307CFT66	208-Lead Plastic Flat Pack (28x28mm)	PRODUCT LAST SHIPMENTS(7)	Sample Pack

[\[top\]](#)

[Home](#) | [Solutions](#) | [Products](#) | [Support](#) | [Contact](#) | [About Us](#) | [Site Map](#)

