



Technical Requirement:

1. Conductor: 7/0.10 AS.
 2. Insulation material: polypropylene, Colour: black, red, green, yellow.
 3. Total length: 2000 ± 50 .
 4. Jacket material: PVC, Color: 132 White.
 5. The end of skin a wire to tin.
 6. No voltage breakdown occurs when tested at 50 HZ 1000V per min.
- Insulation resistance: $\geq 100M\Omega/m$.
- Conductor resistance: $\leq 1.4\Omega/m$.

ITEM	CODE	PART	Q'TY	MATERIAL	NOTE
3		AMOUNT OF CORE	4	Insulation:PP	CONDUCTOR: 7/0.10AS
2		HRBBT-420 FIXEDJACKET WIRE	1	Jacket:PVC	PVC COLOR:132 White
1		MODULAR PLUG 4P4C	1	PC	PLATED: common 3μ "
BADGE	Q'TY	REJIGGER	FILE	NAME	DATE
DESIGN		STANDARD	ZATTON	DRAWING MARK	UNIT SCALE
PROOF		APPROVED		S A A	mm 1: 1
AUDITING		SANCTION			
CRAFTWORK		DATE	17-12-18	TOGETHER SHEET	

**HRBBT-420-4
TELEPHONE COILED CORD**